

## Setup Nightly Back Up and Start Up Options

From the Main Menu select the following options:

- # 7 Files
- #17 Location Master
- # 1 Location Master Maintenance

Select General Environment, Enter

```

South Point Systems Inc.                               Program: LOP01M
Date---: 8/12/03
Time---: 13:33:22
User---: SARAH
Mouse--: * Enabled

NOTE: Changes become effective at Sign On
      or when accessing this Location

WORK WITH/ESTABLISH YOUR SOFTWARE OPERATING ENVIRONMENT
Select Section Description                               Section ID
X      General Environment                               (A)
      Information Pertaining to Accounts Payable        (B)
      Information Pertaining to Human Resources          (C)
      Information Pertaining to General Ledger           (D)
      Information Pertaining to SPSWR (Wholesale/Retail) (E)
      Information Pertaining to SPSMFG (Manufacturing )  (F)
      Information Pertaining to SPSUTL (Public Utilities) (G)

INSTRUCTIONS: Click on/Enter any character by Section(s) you wish to work with
This program allows you to customize the operating environment of your
software. Defaults have been established for you. But since no two businesses
are alike, we allow you to customize features to meet your individual needs.
If you need assistance, please call the South Point Support Line.

Master Record Last Changed on: 7/14/2003 by: JOE

CLICK ON/MARK YOUR SELECTION(s) AND PRESS ENTER TO CONTINUE (+)
F7 - EXIT PROGRAM
  
```

Select Establish Nightly Back Up and Start Up Options, Enter

```

South Point Systems Inc.                               Program: LOP01M
Date---: 8/12/03
Time---: 13:34:22
User---: SARAH
Mouse--: * Enabled

WORK WITH/ESTABLISH GENERAL ENVIRONMENT

Select Section Description                               Section ID
      Establish Overall Location Environment             (AA)
      Establish Printer Environment                     (AB)
      Establish Printkey Defaults                       (WSD01MCL)
      Establish Printer Type Environment                (PRTR1MCL)
      Establish Menu Authorization Environment          (AUTH1MCL)
      Establish File Synchronization Scheme Environment (LOP30MCL)
X      Establish Nightly Back Up and Start Up Options   (AC)
      Establish User Defined Commands to be ran during Back Up (BACK1MCL)
      Work With Current Record Numbers                 (AE)

INSTRUCTIONS: Click on/Enter any character by Section(s) to work with

Information Shared between all South Point Systems Software Products
CLICK ON/MARK YOUR SELECTION(s) AND PRESS ENTER TO CONTINUE (+)
F2 - PAGE BACK (-) F5 - RETURN TO FIRST SCREEN
F7 - EXIT PROGRAM
  
```

Choose Device to save to: \_\_\_\_\_

Save Location Data On: Decide Days of the Week you want to save info on system to a Back Up Tape.

Choose whether or not you want to allow system to be powered down from the Main Menu.

```
South Point Systems Inc.                               Screen 1 of 6 - (AC)
SAVE/STARTUP INFORMATION

Primary Location Library for your software: SPSWRFL1
Current Location Data Library-----: SPSWRFL6
Device for Saving Location Data-----: T9

Save Location Data on-----:
(Enter a tape device and a Y by the day(s) you wish to save your location data)
(The Location Data will be saved during the submitted daily back up )
Allow System to be Powered Down from Menu-: N (Y or N)

The other screens for this section are accessible only from the Primary
Location for your software. If the above Primary Location Library matches the
Current Location Library, you will be able to access the other screens once
you press enter. Otherwise you must sign onto the Primary Location and return
to this program to access the other Save/Startup Information.

PRESS ENTER TO CONTINUE (-)  F7 - EXIT PROGRAM
F1 - UPDATE CHANGES          F14 - WORK WITH TAPE DEVICES
F2 - PAGE BACK                (+)
F5 - 1st SCREEN
```

F1 Update Changes

F7 Exit Program

If you need additional information, email us at [support@southpoint.net](mailto:support@southpoint.net), or call our office.